



ALARM.COM

Alarm.com Smart Chime Data Sheet

ADC-W115C

www.alarm.com

© 2021 Alarm.com. All rights reserved. 210107

Specifications

Wi-Fi Connection: 802.11 b/g/n, 2.4 GHz

Wi-Fi Security: WPA2

LED Indicators: 4

Buttons: WPS, Reset

Antennas: 2 Wi-Fi

Chime: 1.5 W speaker, 77 dB

Operating Temperature: 32°F to 104°F
(0°C to 40°C)

Operating Humidity: 10% to 90%
(non-condensing) RH

Dimensions (H x W x D): With antennas 5.0 x
1.0 x 2.1" (12.7 x 13.0 x 5.4 cm)

Without antennas 3.3 x 3.3 x 2.1" (8.5 x 8.5 x
5.4 cm)



Overview

Designed to work seamlessly with the Alarm.com platform, the ADC-W115C serves as a robust Wi-Fi extender and customizable wireless doorbell chime. Add the Alarm.com Smart Chime to an account when an in-home chime is not a feasible option during a doorbell camera installation. Simply plug the ADC-W115C into a wall outlet, pair with the existing router, add a doorbell camera, and enjoy boosted network signals that provide instantaneous chime notifications.

Features

- Wireless doorbell chime
- Wi-Fi extender (2.4 GHz)
- Adjustable chime volume
- Customizable tones
- Simple, plug-in installation
- Remote management and troubleshooting

In the Box

- ADC-W115C Alarm.com Smart Chime
- Installation Guide

LED Guide

🔌	☁️	📶	🔄	🔌☁️📶🔄
On <i>Device powered on</i>	On <i>Connected to Internet</i>	On <i>Device connected to chime</i>	Off <i>WPS mode not enabled</i>	Blinking (escalating) <i>Firmware upgrade in progress</i>
Off <i>Device powered off</i>	Off <i>No local or Internet connection</i>	Off <i>No device connected to chime</i>	Blinking (slowly) <i>WPS mode enabled to connect to router</i>	Blinking (simultaneously) <i>Reset in progress</i>
Blinking <i>Device booting up</i>	Blinking <i>Local connection, no Internet connection</i>	Blinking (3 quick blinks) <i>Now device connected to chime</i>	Blinking (rapidly) <i>WPS mode enabled to connect to device</i>	
	Blinking (5 quick blinks) <i>Communication test initiated</i>			